



# FR-366K

The microphones in the FR-366K kit were designed with high quality FET pre-amps to ensure outstanding audio quality under even the most demanding conditions. The FR-366K lavalier microphones require 48V phantom power to operate. Phantom power is available from most professional video cameras and mixers.

The FR-366K kit contains 2 different microphones: a cardioid mic with an 8mm capsule and an omni mic with a 6mm capsule. They are both supplied with foam windscreens and clips.

## FEATURES

- > Low noise floor enables clear, natural sound
- > Wide dynamic range Includes one omni mic and one cardioid mic
- > Perfect for interviews, video production and as instrument mics

## SPECIFICATIONS

### FR - 360

Type	Electret Condenser Microphone
Maximum SPL	120 dB
Polar Pattern	Omni-directional
Signal To Noise Ratio	74 dB
Frequency Response	40-18000 Hz
Sensitivity	-42dB±3dB (0dB=1V/Pa, @ 1kHz)
Impedance	200Ω @ 1KHz
Power Requirements	48V Phantom Power
Accessories	Windscreen

### FR - 361

Type	Electret Condenser Microphone
Maximum SPL	120 dB
Polar Pattern	Cardioid
Signal To Noise Ratio	76 dB
Frequency Response	40-18000 Hz
Sensitivity	-42dB±3dB (0dB=1V/Pa, @ 1kHz)
Impedance	200Ω @ 1KHz
Power Requirements	48V Phantom Power
Accessories	Windscreen

