



FR-402

The **MXL FR-402** is a multipurpose boundary mic with a wide pattern and low profile. You can use this mic on a number of different sources in almost any location. It's also right at home on a conference table, recording interviews, connected to a video camera for field recording or capturing audio from a concert or play.

FEATURES

- > Three capsule array
- > Includes 15' mini XLR-to-XLR cable
- > Wide pattern for stage, live performance, interviews, podcasting, and concerts

ACCESSORIES



XLR Cable

SPECIFICATIONS

Type	Boundary mic with 3-capsule array
Polar Pattern	120 degree cardioid
Frequency Response	50Hz - 16kHz
Max SPL	120 dB
Sensitivity	45mV/Pa
Output Impedance	200 ohms
Operating Voltage	48V Phantom Power
Signal-to-Noise Ratio	72 dB
Includes	Bass Cut/Boost switch

